



- Wires: 2 x light blue primary thermoswitch 140⁰C.
 - Wires: 2 x black secondary thermoswitch 80⁰C.
 - Wires: 2 x yellow rectifier thermoswitch 65⁰C.
 - Wires: 1 x brown; 1 x white –secondary toroid current monitor 150 mV/kA ± 3% at 1kΩ ohmic resistance.
- Earthing: if the earth connection MP is removed another suitable kind of protective measure is to be installed.

Type	Output power @x = 20% [kW]	Rated supply voltage U _{1N} [V]	Permanent input current I _{1p} [A]	Turns ratio n	Rectified voltage U _{2d} [V]	Output current [kA]		
						Perma- nent I _{2p}	On 200μΩ load I _{2R}	Nominal @x=20%
MIT-J-130-500/9 TM	130	500	127	51:1	9	6,5	30	15
MIT-J-150-500/10.2 TM	150	500	142	46:1	10.2	6,5	34	15

Admissible output current – see load diagram

Frequency f : 1000Hz

Surge output current I_{FSM}(10ms, T_{jmax} 170⁰) : 100kA

Cooling water :
min. 8 L/min, max. 30 C⁰

Protection class: Transformer IP65, Terminals IP00

Insulation class: F

Mass [Kg]: 17,5

www.isomatic.com
isomatic@isomatic.com
Tel.: +3592-8774-596
Fax: +3592-975-3032

Normative references:
ISO 5826, ISO 10656,
ISO 22829

MF Transformer Rectifier

2008	Name	Date	Issue 1
Drawn	TT	10.07	
Checked	GN	11.07	